



TOURING 11 230V 6V/12V



Обзор

TOURING 11 230V 6V/12V

cod. 807591

Battery charger with electronic control of the charging steps, automatic interruption and restart (TRONIC), for charging WET, GEL, Pb-Ca, AGM, MF, EFB batteries with 6/12V voltage.

With warning LED to indicate battery charge status.

Fit with protection against overloads and polarity reversal and recognition of battery voltage.



1 PH 230V



МАРКИРОВКА CE



СЕРТИФИКАЦИИ EAC

Технические данные

CODE	КОД 807591	A _{EFF}	ТОК ЭФФЕКТИВНОГО ЗАРЯДА 2 / 6 А	W ^H L	РАЗМЕРЫ 10 x 19 x 19 cm
V _{1PH}	ОДНОФАЗНОЕ НАПРЯЖЕНИЕ СЕТИ 230 V	A _{EN}	ТОК КОНВЕНЦИОНАЛЬНОГО ЗАРЯДА EN60335-2-29 1,5 / 3 А	kg	ВЕС 1,757 kg
F	ЧАСТОТЫ СЕТИ 50 / 60 Hz	C _{MIN}	МИН. НОМИНАЛЬНАЯ ССЫЛКА ПОТЕНЦИАЛ 15 / 25 А	BAR CODE	КОД EAN 800489798379 0
P	ПОГЛОЩЕННАЯ МОЩНОСТЬ ЗАРЯДА 60 W	C _{MAX}	МАКС. НОМИНАЛЬНАЯ ССЫЛКА ПОТЕНЦИАЛ 30 / 55 А		ЧАСТЕЙ / ПАЛЛЕТ 168 pz/pallet
	НАПРЯЖЕНИЕ ЗАРЯДКИ 6 / 12 V				